

HobbyWing2205-2600KV-G2

| | | | | | | |
|---------|-------------------|-------|--------|------|-----|-------|
| 电机型号 | 2205-2600KV-G2 | | | | | |
| 定子外径 | 22mm | | | | | |
| 定子厚度 | 5mm | | | | | |
| 定子槽数 | 12 | | | | | |
| 定子极数 | 14 | | | | | |
| 电机KV | 2600 | | | | | |
| 空载电流 | 2.1A | | | | | |
| 电机电阻 | 0.044 Ω | | | | | |
| 最大连续功率 | 420W | | | | | |
| 最大连续电流 | 25A/15s | | | | | |
| 重量 | 29.5g | | | | | |
| 转子直径 | 28.1mm | | | | | |
| 出轴直径 | 5mm | | | | | |
| 电机长度 | 15.8mm | | | | | |
| 电机含轴总长度 | 29.2mm | | | | | |
| 最大电池节数 | 4S | | | | | |
| 推荐使用螺旋桨 | 5045三叶桨 5152三叶桨 | | | | | |
| 建议使用电调 | 30A/3-4S | | | | | |
| 螺旋桨 | 电压 | 电流 | 拉力 | 油门量 | 功率 | 力效 |
| (inch) | (V) | (A) | (g) | (%) | (W) | (g/W) |
| 5*4.5 | 16.8 | 8.78 | 399.6 | 44% | 147 | 2.7 |
| | | 16.34 | 602.2 | 60% | 274 | 2.2 |
| | | 24.68 | 797.3 | 73% | 415 | 1.9 |
| | | 35.07 | 999.4 | 83% | 589 | 1.7 |
| | | 40.93 | 1200.1 | 90% | 688 | 1.7 |
| | | 53.72 | 1437.4 | 100% | 903 | 1.6 |
| 5.1*5.2 | 16.8 | 3.32 | 200.6 | 28% | 56 | 3.6 |
| | | 9.72 | 399.4 | 46% | 163 | 2.4 |
| | | 18.14 | 601.8 | 62% | 305 | 2.0 |
| | | 26.86 | 797.1 | 74% | 451 | 1.8 |
| | | 38.81 | 1000.7 | 87% | 652 | 1.5 |
| | | 58.59 | 1342.6 | 100% | 984 | 1.4 |

